

EXB50 SERIES

Single output

- High efficiency topology, 91% typical on EXB50-48S05
- Industry standard footprint
- Wide operating temperature -40°C to +70°C (natural convection)
- 60% to 110% output trim
- No minimum load
- Overvoltage and overtemperature protection
- Remote sense compensation
- Remote on/off



Distributed By:
B. J. Wolfe Enterprises

www.bjwe.com

(800) 554-1224 • (818) 889-8412

[2 YEAR WARRANTY]



The EXB50 series of 50 Watt single-output isolated DC/DC converters is specifically designed to meet the power needs of low-voltage silicon. Housed in an open-frame package with an industry-standard footprint, these latest-generation converters offer efficiencies as high as 91%. The series comprises three 24V-input models with 5V, 3.3V and 2V outputs, and six 48V-input models with 12V, 5V, 3.3V 2.5V, 2.0V and 1.8V outputs. All models feature a wide input range, trimmable output voltage and a 10A current rating (except the 12V). Remote sense and remote on/off facilities are included as standard, and the converters are comprehensively protected against over-current, over-voltage and over-temperature conditions.

SPECIFICATION

All specifications are typical at nominal input, full load at 25°C unless otherwise stated

OUTPUT SPECIFICATIONS		
Voltage adjustability		60% to 110%
Set point accuracy		±1.5% max.
Line regulation	Low line to high line	0.1% max.
Load regulation	Full load to min. load	0.2% max.
Total error band		±3.0%
Minimum load		0%
Overshoot	At turn-on and turn-off	None
Undershoot		None
Ripple and noise (See Note 1)	5Hz to 20MHz	100mV pk-pk 20mV rms
Transient response (See Notes 2 and 8)	24V models 48V models	3.0% peak deviation 2.0% peak deviation, 200µs recovery to within total error band
Remote sense	(See Note 9)	10% o/p voltage change
INPUT SPECIFICATIONS		
Input voltage range (See Note 14)	24Vin nominal 48Vin nominal 100V 100ms Transient	18 to 36VDC 36 to 75VDC
Input current	24V: No load 24V: Remote OFF 48V: No load 48V: Remote OFF	85mA max. 20mA max. 60mA max. 10mA max.
Input current (max.) (See Note 4)	24V models 48V models	3.25A max. @ Io max. and Vin = 18 to 36V 1.7A max. @ Io max. and Vin = 36 to 75V
Input reflected ripple (See Note 6)	24V models 48V models	20mA (pk-pk) typ. 50mA (pk-pk) typ.
Remote ON/OFF Logic compatibility ON OFF	(See Note 15) Open collector ref to -input Open circuit or >2VDC <1.2VDC	

INPUT SPECIFICATIONS CONTD.		
Undervoltage lockout	24Vin: power up 24Vin: power down 48Vin: power up 48Vin: power down	17Vmax 15Vmin 33.2Vmax 30.9Vmin
Start-up time (See Note 7)	Power up Remote ON/OFF	30ms 25ms
EMC CHARACTERISTICS		
Conducted emissions	EN55022 (See Note 3) EN55022 (See Note 3)	Level A Level B
Radiated emissions	EN55022	Level A
Immunity:	(See Note 13)	
ESD air	EN61000-4-2 8kV (NP), 15kV (RP)	
ESD contact	EN61000-4-2 6kV (NP), 8kV (RP)	
Radiated field enclosure	EN61000-4-3 10V/m (NP)	
Conducted (DC power)	EN61000-4-6 10V (NP)	
Conducted (signal)	EN61000-4-6 10V (NP)	
GENERAL SPECIFICATIONS		
Efficiency		See table
Basic insulation	Input/output	1500VDC
Switching frequency	Fixed	300kHz typ.
Approvals and standards (See Note 5)	IEC60950/EN60950, UL/cUL1950 CSA C22.2 No. 950 Material flammability	UL94V-0
Weight		50g (1.77oz)
MTBF	MIL-HDBK-217F @ 25°C 100% load ground benign	270,000 hours
ENVIRONMENTAL SPECIFICATIONS		
Thermal performance (See Notes 11 & 12)	Operating ambient temperature (natural convection) Non-operating	-40°C to +70°C -55°C to +125°C
ETS 300 019-2-3		Classes T3.1 to T3.5
Altitude (See Note 10)	3,000 metres 10,000 metres	Derate max. output current by 20% Derate max. output current by 50%



Distributed By: B.J. Wolfe Enterprises, Inc.
(800) 554-1224, (818) 889-8412, Fax (818) 889-8417
www.bjwe.com

20 to 50 Watt DC converters

OUTPUT POWER (MAX.)	INPUT VOLTAGE	OVP	OUTPUT VOLTAGE	OUTPUT CURRENT (MIN.)	OUTPUT CURRENT (MAX.)	EFFICIENCY (TYP.)	REGULATION LINE	REGULATION LOAD	MODEL NUMBER
20W	18-36VDC	2.4VDC	2.0V	0A	10A	86.5%	±0.1%	±0.2%	EXB50-24S2V0
33W	18-36VDC	3.9VDC	3.3V	0A	10A	89%	±0.1%	±0.2%	EXB50-24S3V3
50W	18-36VDC	6.0VDC	5.0V	0A	10A	90%	±0.1%	±0.2%	EXB50-24S05
18W	36-75VDC	2.15VDC	1.8V	0A	10A	85.7%	±0.1%	±0.2%	EXB50-48S1V8 ⁽¹⁵⁾
20W	36-75VDC	2.45VDC	2.0V	0A	10A	87.5%	±0.1%	±0.2%	EXB50-48S2V0 ⁽¹⁵⁾
25W	36-75VDC	2.95VDC	2.5V	0A	10A	87.5%	±0.1%	±0.2%	EXB50-48S2V5 ⁽¹⁵⁾
33W	36-75VDC	4.00VDC	3.3V	0A	10A	90.0%	±0.1%	±0.2%	EXB50-48S3V3 ⁽¹⁵⁾
50W	36-75VDC	6.15VDC	5.0V	0A	10A	91.0%	±0.1%	±0.2%	EXB50-48S05 ⁽¹⁵⁾
50W	36-75VDC	14.2VDC	12.0V	0A	4.2A	90.0%	±0.1%	±0.2%	EXB50-48S12 ⁽¹⁵⁾

Notes

- 1 Measured as per recommended set-up. 150mV pk-pk for EXB50-48S12
- 2 di/dt = 0.1A/μs, Vin = 24/48VDC, Tc = 25°C, load change = 0.5 Io max. to 0.75 Io max. and 0.75 Io max. to 0.5 Io max.
- 3 The EXB50 meets level A and level B conducted emissions only with external components connected before the input pins to the converter.
- 4 Recommended input fusing is a 6.3A HRC 200V rated fuse on the 24V and 3.15A HRC 200V rated fuse on the 48V.
- 5 This product is only for inclusion by professional installers within other equipment and must not be operated as a stand alone product.
- 6 Simulated source impedance of 12μH. 12μH inductor in series with +Vin.
- 7 Start-up into resistive load.
- 8 EXB50-24S2V0 model has 5.0% max. deviation and 300μs recovery.
- 9 Maximum output deviation is 10% inclusive of trim.
- 10 Contact factory for operation at higher altitude.
- 11 See Application Note 113 for Derating Curves.
- 12 Wide operating temperature on the EXB50-24S05 is -40°C to +60°C
- 13 Input transient (48V) ETS300 132-2 ETR283
- 14 Applies to 3V3 version only. Please add suffix 'R03' to the model number e.g. EXB50-48S3V3R03. This is also active low remote on/off.
- 15 Active low remote on/off available. Add suffix '-R' to part number.

CAUTION: Hazardous internal voltages and high temperatures.
Ensure that unit is not user accessible.

PROTECTION

Short circuit protection	Continuous
Overvoltage protection	Non-latching clamp
Thermal protection	120°C hot spot temperature with automatic recovery

TELECOM SPECIFICATION

Central office interface A	ETS300-132-2, input voltage and current requirements
----------------------------	--

PIN CONNECTIONS

PIN NO	FUNCTION
1	- Vin
2	No Pin
3	Remote ON/OFF
4	+ Vin
5	+ Vout
6	+ Sense
7	Trim
8	- Sense
9	- Vout

EXTERNAL OUTPUT TRIMMING

Output can be externally trimmed by using the method shown below.

