

Monitoring Relays


1-Phase True RMS AC/DC Over and Under Current

Types DIC01, PIC01

CARLO GAVAZZI



DIC01



PIC01

- TRMS AC/DC over + under, over+over, under+under current and voltage monitoring relays
- DC process signal plus/minus monitoring relay (DIC01)
- Selection of measuring range by DIP-switches
- Adjustable current and voltage on relative scale
- Adjustable hysteresis on relative scale
- Separately adjustable delay functions (0.1 to 30 s)
- Programmable latching or inhibit at set level
- Output: 1 or 2 x 8 A SPDT relay N.D. or N.E. selectable
- For mounting on DIN-rail in accordance with DIN/EN 50 022 (DIC01) or plug-in module (PIC01)
- 45 mm Euronorm housing (DIC01) or 36 mm plug-in module (PIC01)
- LED indication for relay(s), alarm and power supply ON
- Galvanically separated power supply

Product Description

DIC01 and PIC01 are precise TRMS AC/DC over+under, over+over or under+under current and voltage (selectable by DIP-switch) monitoring relays. DIC01 can perform also DC plus/minus measurement by short circuiting pins Z3 and Y1. The devices can be connected to the MI or MP and A82 or E82 current transformers. Both relays have two individual set levels with their own

time delay. Only for DIC01 each set level can work with a single SPDT relay. Owing to the built-in latch function, the ON-position of the relay output can be maintained. Inhibit function can be used to avoid relay operation when not desired (maintenance, transitions). The LED's indicate the state of the alarm and the output relays.

Ordering Key

DIC 01 D B23 AV0

Housing	_____
Function	_____
Type	_____
Item number	_____
Output	_____
Power supply	_____
Range	_____

Type Selection

Mounting	Output	Supply: 24 VDC	Supply: 48 VDC	Supply: 24/48 VAC	Supply: 115/230 VAC
DIN-rail	2xSPDT	DIC 01 D 724 AV0	DIC 01 D 748 AV0	DIC 01 D B48 AV0	DIC 01 D B23 AV0
Plug-in	SPDT	PIC 01 C 724 AV0	PIC 01 C 748 AV0	PIC 01 C B48 AV0	PIC 01 C B23 AV0

Input Specifications

Input				Note 1: The input voltage cannot raise over 300 VAC/DC with respect to ground (PIC01 only)			
Current level		DIC01: Terminals Y1, Y2 PIC01: Terminals 6, 7					
Voltage level		DIC01: Terminals Y1, Y3 PIC01: Terminals 5, 7					
DC levels	(DIC01 only)	Connecting terminals Z3, Y1					
Measuring current ranges				CT ranges MI and MP ranges (0.4 to 4 V _p input)		AAC rms	Max. curr.
Direct		Internal resis.	Max. curr.	1-ph.:	3-ph.:		
Selectable by DIP-switch				MI 5	MP 3005	0.5 to 5 A	20 AAC
0.5 to 5 mA AC/DC		50 Ω	35 mA	MI 20	MP 3020	2 to 20 A	50 AAC
2 to 20 mA AC/DC		50 Ω	55 mA	MI 100	MP 3100	10 to 100 A	250 AAC
-5 to 5 mA DC	(DIC01 only)	50 Ω	35 mA	MI 500	MP 3500	50 to 500 A	750 AAC
-20 to 20 mA DC		50 Ω	55 mA				
Max. current for 1 s		50 Ω	100 mA				
Measuring voltage ranges		Internal resis.	Max. volt.	Note 2: MP 3... current transformers not suitable for under current measurements due to the output signal of the device (see data sheet)			
Direct							
Selectable by DIP-switch							
0.1 to 1 V AC/DC		> 10 kΩ	7 V				
1 to 10 V AC/DC		> 10 kΩ	20 V				
0.4 to 4 V _p AC		> 10 kΩ	100 V				
-1 to 1 VDC	(DIC01 only)	> 10 kΩ	7 V				
-10 to 10 VDC		> 10 kΩ	20 V				
Max. voltage for 1 s			100 V				

Input Specifications (cont.)

CT ranges (cont.)	AAC rms	Max. curr.
A82 ranges (2 to 20 mA input)		
A82-10/20 25	2.5 to 25 A	30 AAC
A82-10/20 50	5 to 50 A	60 AAC
A82-10/20 100	10 to 100 A	120 AAC
A82-10/20 250	25 to 250 A	300 AAC
A82-10/20 500	50 to 500 A	600 AAC
E82-20 ranges (2 to 20 mA input)		
E82-20 25	2.5 to 25 A	50 AAC
E82-20 50	5 to 50 A	100 AAC
Contact input		
DIC01	Terminals Z1, Y1	
PIC01	Terminals 8, 9	
Disabled	> 10 k Ω	
Enabled	< 500 Ω	
Latch disable	> 500 ms	

Output Specifications

Output	1 or 2 x SPDT relays
Rated insulation voltage	250 VAC
Contact ratings (AgSnO ₂)	μ
Resistive loads	AC 1 8 A @ 250 VAC
	DC 12 5 A @ 24 VDC
Small inductive loads	AC 15 2.5 A @ 250 VAC
	DC 13 2.5 A @ 24 VDC
Mechanical life	$\geq 30 \times 10^6$ operations
Electrical life	$\geq 10^5$ operations (at 8 A, 250 V, $\cos \varphi = 1$)
Operating frequency	≤ 7200 operations/h
Dielectric strength	
Dielectric voltage	≥ 2 kVAC (rms)
Rated impulse withstand volt.	4 kV (1.2/50 μ s)

Supply Specifications

Power supply	Overvoltage cat. III (IEC 60664, IEC 60038)	Dielectric voltage	DC supply	AC supply
Rated operational voltage through terminals:		Supply to input	2 kV	4 kV
A1, A2 or A3, A2 (DIC01)		Supply to output	4 kV	4 kV
2, 10 or 11, 10 (PIC01)		Input to output	4 kV	4 kV
724:	24 VDC $\pm 20\%$, insulated	Rated operational power		
748:	48 VDC $\pm 20\%$, insulated	AC	5 VA	
B48:	24/48 VAC $\pm 15\%$	DC	3 W	
	45 to 65 Hz, insulated			
B23:	115/230 VAC $\pm 15\%$			
	45 to 65 Hz, insulated			

General Specifications

Power ON delay	1 s \pm 0.5 s or 6 s \pm 0.5 s	Environment	(EN 60529)
Reaction time	(input signal variation from -20% to +20% or from +20% to -20% of set value)	Degree of protection	IP 20
Alarm ON delay	< 100 ms	Pollution degree	3 (DIC01), 2 (PIC01)
Alarm OFF delay	< 100 ms	Operating temperature	-20 to 60°C, R.H. < 95%
		Storage temperature	-30 to 80°C, R.H. < 95%
Accuracy	(15 min warm-up time)	Housing	
Temperature drift	± 1000 ppm/°C	Dimensions	DIC01 45 x 80 x 99.5 mm
Delay ON alarm	$\pm 10\%$ on set value ± 50 ms		PIC01 36 x 80 x 94 mm
Repeatability	$\pm 0.5\%$ on full-scale	Weight	Approx. 250 g
Indication for		Screw terminals	
Power supply ON	LED, green	Tightening torque	Max. 0.5 Nm acc. to IEC 60947
Alarm ON	LED, red (flashing 2 Hz during delay time)	Approvals	UL, CSA (except 748)
Output relay ON	1 or 2 x LED(s), yellow	CE Marking	Yes
		EMC	
		Immunity	Electromagnetic Compatibility
		Emission	According to EN 61000-6-2 According to EN 61000-6-3

Mode of Operation

DIC01 and PIC01 monitor both AC and DC current and voltage. DIC01 can also monitor positive and negative DC voltage connecting terminals Y1 and Z3.

Example 1
(no contact input - under+over voltage - 2 x SPDT N.D. relays (1 x SPDT for PIC01) - TRMS)
DIC01: One relay operates when the voltage drops below

the under voltage set point for more than the respective delay time. It releases when the voltage exceeds the set level plus the set hysteresis. The other relay operates

when the voltage exceeds the over voltage set point for more than the respective delay time. It releases when the voltage drops below the set level minus hysteresis.

Mode of Operation (cont.)

PIC01: The relay operates when the voltage drops below the under voltage set level for more than the respective set delay time or when it exceeds the over voltage set level for more than the relative set delay time. The relay releases when the voltage exceeds the under voltage set level plus hysteresis and it drops below the over voltage set level minus hysteresis (the hysteresis is the same for both set levels).

Example 2

(latch enable active - under+under current - 2 x SPDT relays (1 x SPDT for PIC01) - TRMS)

DIC01: Each relay operates and latches when the current drops below the respective set level for more than the respective delay time. Provided that the current has exceeded the respective set level plus hysteresis, each relay releases

when the contact input's connection is interrupted.

PIC01: The relay operates when the current drops below the higher set level for more than the respective delay time. Provided that the current has exceeded the higher set level plus hysteresis the relay releases when the contact input's connection is interrupted.

Note

Different delay times can be used for appropriate reaction according to the set points.

Example 3

(inhibit enable active - over+over current with MI CT - DPDT relay (SPDT for PIC01) - TRMS)

Provided that the contact input's connection is interrupted, the relay operates when the current flowing in the MI CT exceeds the lower set level for more than the

respective delay time. It releases when the current drops below the lower set level minus hysteresis or when the contact input's pins are connected.

Example 4

(inhibit enable active - over+over current with A82-10 CT - DPDT relay (1 x SPDT for PIC01) - TRMS)

Provided that the contact input's connection is interrupted, the relay operates when the current flowing in the A82-10 CT exceeds the lower set level for more than its delay time. It releases when the current drops below the lower set level minus hysteresis or when the contact input's pins are connected.

Example 5 (DIC01 only)

(no contact input - under+over voltage - 2 x SPDT N.D. relays

- plus/minus DC

One relay operates when the voltage drops below the under voltage set point for more than the respective delay time. It releases when the voltage exceeds the set level plus the set hysteresis. The other relay operates when the voltage exceeds the over voltage set point for more than the respective delay time. It releases when the voltage drops below the set level minus hysteresis.

In this case the spare front label has to be placed on the device for proper level adjustment.

Note

When the inhibit contact is opened, if the input signal is already in alarm position, the delay time needs to elapse before relay(s) activation.

Function/Range/Level and Time Delay Setting

Adjust the input range setting the DIP switches 1 and 2 of the main black selector as shown below.

Select the desired function setting the DIP switches 3 to 6 of the black selector and 1, 2 of the small red selector as shown below.

To access the DIP switches open the grey plastic cover as shown below

The selection between current and voltage is automatically selected through the input connectors.

TRMS or positive/negative DC monitoring selectable by short-circuiting terminals Y1 and Z3 (DIC01 only).

Selection of level, time delay and hysteresis:

Upper knob:



Setting of hysteresis on relative scale: 0 to 30% on set value.

Centre knobs:

Current level setting on relative scale: 10 to 110% on full scale.

Lower knobs:

Setting of delay on alarm time on absolute scale (0.1 to 30 s).



Measuring range (depending on connections)					
Connect	Input term.	SW1	ON	ON	OFF
None	DIC01: Y1,Y2 PIC01: 5,7	SW2	OFF	ON	ON
Y1 to Z3	DIC01: Y1,Y2		0.5 to 5 mA AC/DC	2 to 20 mA AC/DC	None
None	DIC01: Y1,Y3 PIC01: 6,7		-5 to +5 mA DC	-20 to +20 mA DC	None
Y1 to Z3	DIC01: Y1,Y3		0.1 to 1V AC/DC	4 V _p	1 to 10 V AC/DC
			-1 to +1 V DC	None	-10 to +10 V DC

Set Point 2 (SP2) monitoring function

ON: Over current or voltage
OFF: Under current or voltage

Relay(s) coupling

ON: 2 x SPDT (DIC01 only)
OFF: 1 x DPDT (DIC01, PIC01)

Relay(s) working mode

ON: Normally De-energized (ND)
OFF: Normally Energized (NE)

Power ON delay

ON: 6 s ± 0.5 s
OFF: 1 s ± 0.5 s

Contact input

ON: Latch function enable
OFF: Inhibit function enable


Set Point 1 (SP1) monitoring function

ON: Over current or voltage
OFF: Under current or voltage




Operation Diagrams


Over+over voltage/current - N.D. relay(s)




Over+over voltage/current - Latch - N.D. relay(s)




Over+under voltage/current - N.E. relay(s)



Over+under voltage/current - Inhibit - N.E. relay(s)




Under+under voltage/current - N.D. relay(s)




Wiring Diagrams


Example 1




Example 2




Example 3



Example 4




Example 5




DIC01


Example 1




Example 2



Example 3



Example 4



PIC01



Dimensions

