



SANYO Semiconductors

DATA SHEET

LA6574H — Monolithic Linear IC

Five-Channel Driver (four BTL channels plus one H bridge channel) for MD and CD Player

Overview

The LA6574H is a motor driver IC for MD and CD players with four BTL channels and one H bridge channel. The LA6574H features a separate power supply for the H bridge block, an output adjustment pin, and a 3.3 V regulator to support a wide range of applications.

Functions and Features

- Four power amplifier channels plus one H bridge channel
- I_O max: 700 mA (each channel)
- Built-in level shifting circuits for the BLT amplifiers
- Thermal protection circuit (Thermal shutdown circuit)
- Separate loading block power supply
- Built-in 3.3 V regulator
- Provides a dedicated pin for adjusting the loading block output.

Specifications

Maximum Ratings at $T_a = 25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
Supply voltage	V_{CC} max		14	V
Allowable power dissipation	P_{dmax}	Independent IC	0.82	W
		* Mounted on a board.	2.0	W
Maximum output current	I_O max	Each channel for CH1 to CH5	0.7	A
Maximum input voltage	V_{INB}		13	V
MUTE pin voltage	V_{MUTE}		13	V
Operating temperature	T_{opr}		-30 to +85	$^\circ\text{C}$
Storage temperature	T_{stg}		-55 to +150	$^\circ\text{C}$

Note *: Mounted on a board (76.1 × 114.3 × 1.6 mm) Material: glass epoxy

Recommended Operating Conditions at $T_a = 25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
Supply voltage	V_{CC}		5.6 to 13	V

- Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.
- SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

SANYO Electric Co., Ltd. Semiconductor Company

TOKYO OFFICE Tokyo Bldg., 1-10, 1 chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN

LA6574H

Electrical Characteristics at $T_a = 25^\circ\text{C}$, $V_{CC1} = V_{CC2} = 8\text{ V}$, $V_{REF} = 1.65\text{ V}$

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
[Overall Characteristics]						
No load current drain - ICC on	ICC-ON	All outputs on, FWD = REV = 0 V *1		30	50	mA
VREF input voltage range	VREF-IN		1		VCC-1.5	V
[BTL Amplifier Block]						
Output offset voltage	VOFF	BTL amplifiers, the voltage difference across each channel's output	-50		+50	mV
Input voltage range	VIN	Input resistance: 11 kΩ	0		VCC	V
Output voltage	VO	The voltage between each of the VO+/VO- pairs when RL is 8 Ω. *2	4	5		V
Closed loop voltage gain	VG	Gain from input to output		4		Multi-plier
Slew rate	SR	With the amplifier operating independently, twice the value measured between outputs *4		0.5		V/μs
[H Bridge Block]						
Output voltage	VO-LOAD	The voltage between each of the VO+/VO- pairs when RL is 8 Ω. *2		6		V
Low-level input voltage	VIN-L				1	V
High-level input voltage	VIN-H		2			V
Output control voltage	VCONT	VCONT = 3 V *2		3.5		V
[Regulator Block]						
Output voltage	Vreg	IL = 100 mA	3.05	3.3	3.55	V
Load regulation	ΔVRL	IL = 0 to 200 mA	-50	0	+10	mV
Line regulation	ΔVVCC	VCC = 6 to 12 V, IL = 100 mA	-15	+21	+60	mV

Note *1: The total current drain for V_{CC1} and V_{CC2} with no load.

*2: Voltage difference across the load (8 Ω). With the outputs in the saturated state.



*3: When the MUTE pin is high, the outputs will be on, and when low, the outputs will be off (high-impedance state).

*4: Design guarantee value

Package Dimensions

unit: mm

3234B



LA6574H

Pin Functions

Pin No.	Symbol	Pin descriptions
1	V _{CC2}	Channels 3, 4, and 5 power supply (This pin must be shorted to V _{CC1} and V _{CC-S} .)
2	V _{O5-}	Loading output (-)
3	V _{O5+}	Loading output (+)
4	V _{O4+}	Channel 4 output (+)
5	V _{O4-}	Channel 4 output (-)
6	V _{O3+}	Channel 3 output (+)
7	V _{O3-}	Channel 3 output (-)
8	V _{O2+}	Channel 2 output (+)
9	V _{O2-}	Channel 2 output (-)
10	V _{O1+}	Channel 1 output (+)
11	V _{O1-}	Channel 1 output (-)
12	V _{CC1}	Channels 1 and 2 (BTL) power supply (This pin must be shorted to V _{CC-S} and V _{CC2} .)
13	V _{IN1}	Channel 1 input
14	V _{IN1G}	Channel 1 input (gain adjustment input)
15	V _{IN2}	Channel 2 input
16	V _{IN2G}	Channel 2 input (gain adjustment input)
17	V _{IN3}	Channel 3 input
18	V _{IN3G}	Channel 3 input (gain adjustment input)
19	REG-IN	Regulator input (external pnp transistor base)
20	REG-OUT	Regulator output (external pnp transistor collector)
21	VREF-IN	Reference voltage input
22	V _{CC-S}	Signal system power supply (This pin must be shorted to V _{CC1} and V _{CC2} .)
23	V _{IN4G}	Channel 4 input (gain adjustment input)
24	V _{IN4}	Channel 4 input
25	VCONT	Channel 5 (VLO) output voltage control
26	S-GND	Signal system ground
27	FWD	Channel 5 (VLO) output switching (FWD); loading block logic input
28	REV	Channel 5 (VLO) output switching (REV); loading block logic input


- Note:
- The center frame (FR) is used as the power system ground. Along with the signal system ground (S-GND), this level must be the lowest potential in the system.
 - The three power supply pins V_{CC-S}, V_{CC1}, and V_{CC2} must be shorted together externally.

Pin Functions


Pin No.	Symbol	Pin name	Pin description	Equivalent circuit
13 14 15 16 17 18 23 24	V_{IN}	Inputs	Inputs	
4 5 6 7 8 9 10 11	V_O	Outputs	Outputs	
2 3 25	V_{O5+} V_{O5-} V_{CONT}	V_{O5}	H bridge outputs	
27 28	FWD REV	FWD REV	H bridge inputs	

LA6574H

Block Diagram



Sample Application Circuit



H Bridge Block


FWD	REV	V _{O5+}	V _{O5-}	Mode
L	L	OFF	OFF	Open *1
L	H	H	L	Forward
H	L	L	H	Reverse
H	H	L	L	Brake *2

Note *1: The output are in the high-impedance state in this mode

*2: In brake mode, the sink side transistors are on (short-circuit braking). The V_{LO+} and V_{LO-} levels go to a level essentially the same as the ground level.

*3: V_{CONT} (output voltage setting pin) and V_{LO} have the following relationship: $V_{LO} = V_{CONT} - 1 \text{ V}$ (typical)

Relationship between the MUTE pin and the power supplies (V_{CC}*)



- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, of otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or

This catalog provides information as of August, 2004. Specifications and information herein are subject to change without notice.