STK14C88

32K x 8 *AutoStore*™ nvSRAM *QuantumTrap*™ CMOS Nonvolatile Static RAM

FEATURES

- **25ns, 35ns and 45ns Access Times**
- **"Hands-off" Automatic *STORE* with External 68μF Capacitor on Power Down**
- ***STORE* to nonvolatile elements Initiated by Hardware, Software or *AutoStore*™**
- ***RECALL* to SRAM Initiated by Software or Power Restore**
- **10mA Typical I_{CC} at 200ns Cycle Time**
- **Unlimited READ, WRITE and *RECALL* Cycles**
- **1,000,000 *STORE* Cycles to nonvolatile elements (Commercial/Industrial)**
- **100-Year Data Retention in nonvolatile elements (Commercial/Industrial)**
- **Single 5V ± 10% Operation**
- **Commercial, Industrial and Military Temperatures**
- **32-Pin SOIC, DIP and LCC Packages**

DESCRIPTION

The Simtek STK14C88 is a fast static RAM with a nonvolatile element incorporated in each static memory cell. The SRAM can be read and written an unlimited number of times, while independent, nonvolatile data resides in the nonvolatile elements. Data transfers from the SRAM to the nonvolatile elements (the *STORE* operation) can take place automatically on power down. A 68μF or larger capacitor tied from V_{CAP} to ground guarantees the *STORE* operation, regardless of power-down slew rate or loss of power from "hot swapping". Transfers from the nonvolatile elements to the SRAM (the *RECALL* operation) take place automatically on restoration of power. Initiation of *STORE* and *RECALL* cycles can also be software controlled by entering specific read sequences. A hardware *STORE* may be initiated with the $\overline{HSB}$ pin.

BLOCK DIAGRAM



PIN CONFIGURATIONS



32 - LCC

32 - DIP
32 - SOIC

PIN NAMES

A_0 - A_{14}	Address Inputs
DQ_0 -DQ_7	Data In/Out
$\overline{E}$	Chip Enable
$\overline{W}$	Write Enable
$\overline{G}$	Output Enable
$\overline{HSB}$	Hardware Store Busy (I/O)
V_{CCX}	Power (+ 5V)
V_{CAP}	Capacitor
V_{SS}	Ground

ABSOLUTE MAXIMUM RATINGS[a]

Voltage on Input Relative to Ground . . . . . –0.5V to 7.0V
Voltage on Input Relative to V_{SS} . . . . . –0.6V to (V_{CC} + 0.5V)
Voltage on DQ_{0-7} or $\overline{HSB}$ . . . . . –0.5V to (V_{CC} + 0.5V)
Temperature under Bias. . . . . –55°C to 125°C
Storage Temperature . . . . . –65°C to 150°C
Power Dissipation 1W
DC Output Current (1 output at a time, 1s duration) 15mA

Note a: Stresses greater than those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only, and functional operation of the device at conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

DC CHARACTERISTICS

(V_{CC} = 5.0V ± 10%)[e]

SYMBOL	PARAMETER	COMMERCIAL		INDUSTRIAL/ Military		UNITS	NOTES
		MIN	MAX	MIN	MAX		
I_{CC_1}[b]	Average V_{CC} Current		97 80 70		100 85 70	mA mA mA	t_{AVAV} = 25ns t_{AVAV} = 35ns t_{AVAV} = 45ns
I_{CC_2}[c]	Average V_{CC} Current during *STORE*		3		3	mA	All Inputs Don't Care, V_{CC} = max
I_{CC_3}[b]	Average V_{CC} Current at t_{AVAV} = 200ns 5V, 25°C, Typical		10		10	mA	$\overline{W} \geq (V_{CC} - 0.2V)$ All Others Cycling, CMOS Levels
I_{CC_4}[c]	Average V_{CAP} Current during *AutoStore*™ Cycle		2		2	mA	All Inputs Don't Care
I_{SB_1}[d]	Average V_{CC} Current (Standby, Cycling TTL Input Levels)		30 25 22		31 26 23	mA mA mA	t_{AVAV} = 25ns, $\overline{E} \geq V_{IH}$ t_{AVAV} = 35ns, $\overline{E} \geq V_{IH}$ t_{AVAV} = 45ns, $\overline{E} \geq V_{IH}$
I_{SB_2}[d]	V_{CC} Standby Current (Standby, Stable CMOS Input Levels)		1.5		1.5	mA	$\overline{E} \geq (V_{CC} - 0.2V)$ All Others $V_{IN} \leq 0.2V$ or $\geq (V_{CC} - 0.2V)$
I_{ILK}	Input Leakage Current		±1		±1	µA	V_{CC} = max $V_{IN} = V_{SS}$ to V_{CC}
I_{OLK}	Off-State Output Leakage Current		±5		±5	µA	V_{CC} = max $V_{IN} = V_{SS}$ to V_{CC}, $\overline{E}$ or $\overline{G} \geq V_{IH}$
V_{IH}	Input Logic "1" Voltage	2.2	V_{CC} + .5	2.2	V_{CC} + .5	V	All Inputs
V_{IL}	Input Logic "0" Voltage	V_{SS} – .5	0.8	V_{SS} – .5	0.8	V	All Inputs
V_{OH}	Output Logic "1" Voltage	2.4		2.4		V	I_{OUT} = –4mA except $\overline{HSB}$
V_{OL}	Output Logic "0" Voltage		0.4		0.4	V	I_{OUT} = 8mA except $\overline{HSB}$
V_{BL}	Logic "0" Voltage on $\overline{HSB}$ Output		0.4		0.4	V	I_{OUT} = 3mA
T_A	Operating Temperature	0	70	–40/-55	85/125	°C	

Note b: I_{CC_1} and I_{CC_3} are dependent on output loading and cycle rate. The specified values are obtained with outputs unloaded.
Note c: I_{CC_2} and I_{CC_4} are the average currents required for the duration of the respective *STORE* cycles (t_{STORE}).
Note d: $\overline{E} \geq V_{IH}$ will not produce standby current levels until any nonvolatile cycle in progress has timed out.
Note e: V_{CC} reference levels throughout this datasheet refer to V_{CCX} if that is where the power supply connection is made, or V_{CAP} if V_{CCX} is connected to ground.

AC TEST CONDITIONS

Input Pulse Levels . . . . . 0V to 3V
Input Rise and Fall Times. . . . . ≤ 5ns
Input and Output Timing Reference Levels 1.5V
Output Load . . . . . See Figure 1

CAPACITANCE[f] (T_A = 25°C, f = 1.0MHz)

SYMBOL	PARAMETER	MAX	UNITS	CONDITIONS
C_{IN}	Input Capacitance	5	pF	ΔV = 0 to 3V
C_{OUT}	Output Capacitance	7	pF	ΔV = 0 to 3V

Note f: These parameters are guaranteed but not tested.



Figure 1: AC Output Loading

SRAM READ CYCLES #1 & #2

(V_{CC} = 5.0V ± 10%)[e]

NO.	SYMBOLS		PARAMETER	STK14C88-25		STK14C88-35		STK14C88-45		UNITS
	#1, #2	Alt.		MIN	MAX	MIN	MAX	MIN	MAX	
1	t_{ELQV}	t_{ACS}	Chip Enable Access Time		25		35		45	ns
2	t_{AVAV}[g]	t_{RC}	Read Cycle Time	25		35		45		ns
3	t_{AVQV}[h]	t_{AA}	Address Access Time		25		35		45	ns
4	t_{GLQV}	t_{OE}	Output Enable to Data Valid		10		15		20	ns
5	t_{AXQX}[h]	t_{OH}	Output Hold after Address Change	5		5		5		ns
6	t_{ELQX}	t_{LZ}	Chip Enable to Output Active	5		5		5		ns
7	t_{EHQZ}[i]	t_{HZ}	Chip Disable to Output Inactive		10		13		15	ns
8	t_{GLQX}	t_{OLZ}	Output Enable to Output Active	0		0		0		ns
9	t_{GHQZ}[i]	t_{OHZ}	Output Disable to Output Inactive		10		13		15	ns
10	t_{ELICCH}[f]	t_{PA}	Chip Enable to Power Active	0		0		0		ns
11	t_{EHICCL}[f]	t_{PS}	Chip Disable to Power Standby		25		35		45	ns

Note g: $\overline{W}$ and $\overline{HSB}$ must be high during SRAM READ cycles and low during SRAM WRITE cycles.
Note h: I/O state assumes $\overline{E}$ and $\overline{G} \leq V_{IL}$ and $\overline{W} \geq V_{IH}$; device is continuously selected.
Note i: Measured ± 200mV from steady state output voltage.

SRAM READ CYCLE #1: Address Controlled[g, h]



SRAM READ CYCLE #2: $\overline{E}$ Controlled[g]



SRAM WRITE CYCLES #1 & #2

(V_{CC} = 5.0V ± 10%)[e]

NO.	SYMBOLS			PARAMETER	STK14C88-25		STK14C88-35		STK14C88-45		UNITS
	#1	#2	Alt.		MIN	MAX	MIN	MAX	MIN	MAX	
12	t_{AVAV}	t_{AVAV}	t_{WC}	Write Cycle Time	25		35		45		ns
13	t_{WLWH}	t_{WLEH}	t_{WP}	Write Pulse Width	20		25		30		ns
14	t_{ELWH}	t_{ELEH}	t_{CW}	Chip Enable to End of Write	20		25		30		ns
15	t_{DVWH}	t_{DVEH}	t_{DW}	Data Set-up to End of Write	10		12		15		ns
16	t_{WHDX}	t_{EHDX}	t_{DH}	Data Hold after End of Write	0		0		0		ns
17	t_{AVWH}	t_{AVEH}	t_{AW}	Address Set-up to End of Write	20		25		30		ns
18	t_{AVWL}	t_{AVEL}	t_{AS}	Address Set-up to Start of Write	0		0		0		ns
19	t_{WHAX}	t_{EHAX}	t_{WR}	Address Hold after End of Write	0		0		0		ns
20	t_{WLQZ}[i, j]		t_{WZ}	Write Enable to Output Disable		10		13		15	ns
21	t_{WHQX}		t_{OW}	Output Active after End of Write	5		5		5		ns

Note j: If $\overline{W}$ is low when $\overline{E}$ goes low, the outputs remain in the high-impedance state.
Note k: $\overline{E}$ or $\overline{W}$ must be ≥ V_{IH} during address transitions.
Note l: $\overline{HSB}$ must be high during SRAM WRITE cycles.

SRAM WRITE CYCLE #1: $\overline{W}$ Controlled[k, l]



SRAM WRITE CYCLE #2: $\overline{E}$ Controlled[k, l]



HARDWARE MODE SELECTION

$\overline{E}$	$\overline{W}$	$\overline{HSB}$	A_{13} - A_0 (hex)	MODE	I/O	POWER	NOTES
H	X	H	X	Not Selected	Output High Z	Standby	
L	H	H	X	Read SRAM	Output Data	Active	t
L	L	H	X	Write SRAM	Input Data	Active	
X	X	L	X	Nonvolatile *STORE*	Output High Z	I_{CC_2}	m

Note m: $\overline{HSB}$ *STORE* operation occurs only if an SRAM WRITE has been done since the last nonvolatile cycle. After the *STORE* (if any) completes, the part will go into standby mode, inhibiting all operations until $\overline{HSB}$ rises.

HARDWARE *STORE* CYCLE

(V_{CC} = 5.0V ± 10%)[e]

NO.	SYMBOLS		PARAMETER	STK14C88		UNITS	NOTES
	Standard	Alternate		MIN	MAX		
22	t_{STORE}	t_{HLHZ}	*STORE* Cycle Duration		10	ms	i, n
23	t_{DELAY}	t_{HLQZ}	Time Allowed to Complete SRAM Cycle	1		µs	i, n
24	$t_{RECOVER}$	t_{HHQX}	Hardware *STORE* High to Inhibit Off		700	ns	n, o
25	t_{HLHX}		Hardware *STORE* Pulse Width	15		ns	
26	t_{HLBL}		Hardware *STORE* Low to *STORE* Busy		300	ns	

Note n: $\overline{E}$ and $\overline{G}$ low and $\overline{W}$ high for output behavior.
Note o: $t_{RECOVER}$ is only applicable after t_{STORE} is complete.

HARDWARE *STORE* CYCLE



AutoStore™/POWER-UP *RECALL*

(V_{CC} = 5.0V ± 10%)[e]

NO.	SYMBOLS		PARAMETER	STK14C88		UNITS	NOTES
	Standard	Alternate		MIN	MAX		
27	$t_{RESTORE}$		Power-up *RECALL* Duration		550	µs	p
28	t_{STORE}	t_{HLHZ}	*STORE* Cycle Duration		10	ms	n, q
29	t_{VSBL}		Low Voltage Trigger (V_{SWITCH}) to $\overline{HSB}$ Low		300	ns	l
30	t_{DELAY}	t_{BLQZ}	Time Allowed to Complete SRAM Cycle	1		µs	n
31	V_{SWITCH}		Low Voltage Trigger Level	4.0	4.5	V	
32	V_{RESET}		Low Voltage Reset Level		3.6	V	

Note p: $t_{RESTORE}$ starts from the time V_{CC} rises above V_{SWITCH}.
Note q: $\overline{HSB}$ is asserted low for 1µs when V_{CAP} drops through V_{SWITCH}. If an SRAM WRITE has not taken place since the last nonvolatile cycle, $\overline{HSB}$ will be released and no *STORE* will take place.

AutoStore™/POWER-UP *RECALL*



SOFTWARE *STORE*/*RECALL* MODE SELECTION

$\overline{E}$	$\overline{W}$	A_{13} - A_0 (hex)	MODE	I/O	POWER	NOTES
L	H	0E38	Read SRAM	Output Data	Active	r, s, t
		31C7	Read SRAM	Output Data		
		03E0	Read SRAM	Output Data		
		3C1F	Read SRAM	Output Data		
		303F	Read SRAM	Output Data		
		0FC0	Nonvolatile *STORE*	Output High Z	I_{CC_2}	
L	H	0E38	Read SRAM	Output Data	Active	r, s, t
		31C7	Read SRAM	Output Data		
		03E0	Read SRAM	Output Data		
		3C1F	Read SRAM	Output Data		
		303F	Read SRAM	Output Data		
		0C63	Nonvolatile *RECALL*	Output High Z		

SOFTWARE-CONTROLLED *STORE*/*RECALL* CYCLE[v] (V_{CC} = 5.0V ± 10%)[e]

NO.	SYMBOLS		PARAMETER	STK14C88-25		STK14C88-35		STK14C88-45		UNITS	NOTES
	Standard	Alternate		MIN	MAX	MIN	MAX	MIN	MAX		
33	t_{AVAV}	t_{RC}	*STORE*/*RECALL* Initiation Cycle Time	25		35		45		ns	n
34	t_{AVEL}	t_{AS}	Address Set-up Time	0		0		0		ns	u
35	t_{ELEH}	t_{CW}	Clock Pulse Width	20		25		30		ns	u
36	t_{ELAX}		Address Hold Time	20		20		20		ns	u
37	t_{RECALL}		*RECALL* Duration		20		20		20	µs	

Note r: The six consecutive addresses must be in the order listed. $\overline{W}$ must be high during all six consecutive cycles to enable a nonvolatile cycle.
Note s: While there are 15 addresses on the STK14C88, only the lower 14 are used to control software modes.
Note t: I/O state assumes $\overline{G} \leq V_{IL}$. Activation of nonvolatile cycles does not depend on state of $\overline{G}$.
Note u: The software sequence is clocked with $\overline{E}$ controlled READs.
Note v: The six consecutive addresses must be in the order listed in the Hardware Mode Selection Table: (0E38, 31C7, 03E0, 3C1F, 303F, 0FC0) for a *STORE* cycle or (0E38, 31C7, 03E0, 3C1F, 303F, 0C63) for a *RECALL* cycle. $\overline{W}$ must be high during all six consecutive cycles.

SOFTWARE *STORE*/*RECALL* CYCLE: $\overline{E}$ CONTROLLED[v]



DEVICE OPERATION

The STK14C88 has two separate modes of operation: SRAM mode and nonvolatile mode. In SRAM mode, the memory operates as a standard fast static RAM. In nonvolatile mode, data is transferred from SRAM to nonvolatile elements (the *STORE* operation) or from nonvolatile elements to SRAM (the *RECALL* operation). In this mode SRAM functions are disabled.

NOISE CONSIDERATIONS

The STK14C88 is a high-speed memory and so must have a high-frequency bypass capacitor of approximately 0.1µF connected between V_{CAP} and V_{SS}, using leads and traces that are as short as possible. As with all high-speed CMOS ICs, normal careful routing of power, ground and signals will help prevent noise problems.

SRAM READ

The STK14C88 performs a READ cycle whenever $\overline{E}$ and $\overline{G}$ are low and $\overline{W}$ and $\overline{HSB}$ are high. The address specified on pins A_{0-14} determines which of the 32,768 data bytes will be accessed. When the READ is initiated by an address transition, the outputs will be valid after a delay of t_{AVQV} (READ cycle #1). If the READ is initiated by $\overline{E}$ or $\overline{G}$, the outputs will be valid at t_{ELQV} or at t_{GLQV}, whichever is later (READ cycle #2). The data outputs will repeatedly respond to address changes within the t_{AVQV} access time without the need for transitions on any control input pins, and will remain valid until another address change or until $\overline{E}$ or $\overline{G}$ is brought high, or $\overline{W}$ or $\overline{HSB}$ is brought low.

SRAM WRITE

A WRITE cycle is performed whenever $\overline{E}$ and $\overline{W}$ are low and $\overline{HSB}$ is high. The address inputs must be stable prior to entering the WRITE cycle and must remain stable until either $\overline{E}$ or $\overline{W}$ goes high at the end of the cycle. The data on the common I/O pins DQ_{0-7} will be written into the memory if it is valid t_{DVWH} before the end of a $\overline{W}$ controlled WRITE or t_{DVEH} before the end of an $\overline{E}$ controlled WRITE.

It is recommended that $\overline{G}$ be kept high during the entire WRITE cycle to avoid data bus contention on common I/O lines. If $\overline{G}$ is left low, internal circuitry will turn off the output buffers t_{WLQZ} after $\overline{W}$ goes low.

POWER-UP *RECALL*

During power up, or after any low-power condition (V_{CAP} < V_{RESET}), an internal *RECALL* request will be latched. When V_{CAP} once again exceeds the sense voltage of V_{SWITCH}, a *RECALL* cycle will automatically be initiated and will take $t_{RESTORE}$ to complete.

If the STK14C88 is in a WRITE state at the end of power-up *RECALL*, the SRAM data will be corrupted. To help avoid this situation, a 10K Ohm resistor should be connected either between $\overline{W}$ and system V_{CC} or between $\overline{E}$ and system V_{CC}.

SOFTWARE NONVOLATILE *STORE*

The STK14C88 software *STORE* cycle is initiated by executing sequential $\overline{E}$ controlled READ cycles from six specific address locations. During the *STORE* cycle an erase of the previous nonvolatile data is first performed, followed by a program of the nonvolatile elements. The program operation copies the SRAM data into nonvolatile memory. Once a *STORE* cycle is initiated, further input and output are disabled until the cycle is completed.

Because a sequence of READs from specific addresses is used for *STORE* initiation, it is important that no other READ or WRITE accesses intervene in the sequence, or the sequence will be aborted and no *STORE* or *RECALL* will take place.

To initiate the software *STORE* cycle, the following READ sequence must be performed:

1.	Read address	0E38 (hex)	Valid READ
2.	Read address	31C7 (hex)	Valid READ
3.	Read address	03E0 (hex)	Valid READ
4.	Read address	3C1F (hex)	Valid READ
5.	Read address	303F (hex)	Valid READ
6.	Read address	0FC0 (hex)	Initiate *STORE* cycle

The software sequence must be clocked with $\overline{E}$ controlled READs.

Once the sixth address in the sequence has been entered, the *STORE* cycle will commence and the chip will be disabled. It is important that READ cycles and not WRITE cycles be used in the sequence, although it is not necessary that $\overline{G}$ be low for the sequence to be valid. After the t_{STORE} cycle time has been fulfilled, the SRAM will again be activated for READ and WRITE operation.

SOFTWARE NONVOLATILE *RECALL*

A software *RECALL* cycle is initiated with a sequence of READ operations in a manner similar to the software *STORE* initiation. To initiate the *RECALL* cycle, the following sequence of $\overline{E}$ controlled READ operations must be performed:

1.	Read address	0E38 (hex)	Valid READ
2.	Read address	31C7 (hex)	Valid READ
3.	Read address	03E0 (hex)	Valid READ
4.	Read address	3C1F (hex)	Valid READ
5.	Read address	303F (hex)	Valid READ
6.	Read address	0C63 (hex)	Initiate *RECALL* cycle

Internally, *RECALL* is a two-step procedure. First, the SRAM data is cleared, and second, the nonvolatile information is transferred into the SRAM cells. After the t_{RECALL} cycle time the SRAM will once again be ready for READ and WRITE operations. The *RECALL* operation in no way alters the data in the nonvolatile elements. The nonvolatile data can be recalled an unlimited number of times.

AutoStore™ OPERATION

The STK14C88 can be powered in one of three modes.

During normal *AutoStore*™ operation, the STK14C88 will draw current from V_{CCX} to charge a capacitor connected to the V_{CAP} pin. This stored charge will be used by the chip to perform a single *STORE* operation. After power up, when the voltage on the V_{CAP} pin drops below V_{SWITCH}, the part will automatically disconnect the V_{CAP} pin from V_{CCX} and initiate a *STORE* operation.

Figure 2 shows the proper connection of capacitors for automatic store operation. A charge storage capacitor having a capacity of between 68µF and 220µF (± 20%) rated at 6V should be provided.

In system power mode (Figure 3), both V_{CCX} and V_{CAP} are connected to the + 5V power supply without the 68µF capacitor. In this mode the *AutoStore*™ function of the STK14C88 will operate on the stored system charge as power goes down. The user must, however, guarantee that V_{CCX} does not drop below 3.6V during the 10ms *STORE* cycle.

If an automatic *STORE* on power loss is not required, then V_{CCX} can be tied to ground and + 5V applied to V_{CAP} (Figure 4). This is the *AutoStore*™ Inhibit mode, in which the *AutoStore*™ function is disabled. If the STK14C88 is operated in this configuration, references to V_{CCX} should be changed to V_{CAP} throughout this data sheet. In this mode, *STORE* operations may be triggered through software control or the $\overline{HSB}$ pin. It is not permissable to change between these three options “on the fly”.

In order to prevent unneeded *STORE* operations, automatic *STORE*s as well as those initiated by externally driving $\overline{HSB}$ low will be ignored unless at least one WRITE operation has taken place since the most recent *STORE* or *RECALL* cycle. Software-initiated *STORE* cycles are performed regardless of whether a WRITE operation has taken place. An optional pull-up resistor is shown connected to $\overline{HSB}$. This can be used to signal the system that the *AutoStore*™ cycle is in progress.



Figure 2: *AutoStore*™ Mode



Figure 3: System Power Mode



Figure 4: *AutoStore*™ Inhibit Mode

*If $\overline{HSB}$ is not used, it should be left unconnected.

If the power supply drops faster than 20 µs/volt before V_{CCX} reaches V_{SWITCH}, then a 2.2 ohm resistor should be inserted between V_{CCX} and the system supply to avoid momentary excess of current between Vccx and Vcap.

$\overline{\text{HSB}}$ OPERATION

The STK14C88 provides the $\overline{\text{HSB}}$ pin for controlling and acknowledging the *STORE* operations. The $\overline{\text{HSB}}$ pin can be used to request a hardware *STORE* cycle. When the $\overline{\text{HSB}}$ pin is driven low, the STK14C88 will conditionally initiate a *STORE* operation after t_{DELAY}; an actual *STORE* cycle will only begin if a WRITE to the SRAM took place since the last *STORE* or *RECALL* cycle. The $\overline{\text{HSB}}$ pin also acts as an open drain driver that is internally driven low to indicate a busy condition while the *STORE* (initiated by any means) is in progress.

SRAM READ and WRITE operations that are in progress when $\overline{\text{HSB}}$ is driven low by any means are given time to complete before the *STORE* operation is initiated. After $\overline{\text{HSB}}$ goes low, the STK14C88 will continue SRAM operations for t_{DELAY}. During t_{DELAY}, multiple SRAM READ operations may take place. If a WRITE is in progress when $\overline{\text{HSB}}$ is pulled low it will be allowed a time, t_{DELAY}, to complete. However, any SRAM WRITE cycles requested after $\overline{\text{HSB}}$ goes low will be inhibited until $\overline{\text{HSB}}$ returns high.

The $\overline{\text{HSB}}$ pin can be used to synchronize multiple STK14C88s while using a single larger capacitor. To operate in this mode the $\overline{\text{HSB}}$ pin should be connected together to the $\overline{\text{HSB}}$ pins from the other STK14C88s. An external pull-up resistor to + 5V is required since $\overline{\text{HSB}}$ acts as an open drain pull down. The V_{CAP} pins from the other STK14C88 parts can be tied together and share a single capacitor. The capacitor size must be scaled by the number of devices connected to it. When any one of the STK14C88s detects a power loss and asserts $\overline{\text{HSB}}$, the common $\overline{\text{HSB}}$ pin will cause all parts to request a *STORE* cycle (a *STORE* will take place in those STK14C88s that have been written since the last nonvolatile cycle).

During any *STORE* operation, regardless of how it was initiated, the STK14C88 will continue to drive the $\overline{\text{HSB}}$ pin low, releasing it only when the *STORE* is complete. Upon completion of the *STORE* operation the STK14C88 will remain disabled until the $\overline{\text{HSB}}$ pin returns high.

If $\overline{\text{HSB}}$ is not used, it should be left unconnected.

PREVENTING STORES

The *STORE* function can be disabled on the fly by holding $\overline{\text{HSB}}$ high with a driver capable of sourcing 30mA at a V_{OH} of at least 2.2V, as it will have to overpower the internal pull-down device that drives $\overline{\text{HSB}}$ low for 20µs at the onset of a *STORE*. When the STK14C88 is connected for *AutoStore*™ operation (system V_{CC} connected to V_{CCX} and a 68µF capacitor on V_{CAP}) and V_{CC} crosses V_{SWITCH} on the way down, the STK14C88 will attempt to pull $\overline{\text{HSB}}$ low; if $\overline{\text{HSB}}$ doesn't actually get below V_{IL}, the part will stop trying to pull $\overline{\text{HSB}}$ low and abort the *STORE* attempt.

HARDWARE PROTECT

The STK14C88 offers hardware protection against inadvertent *STORE* operation and SRAM WRITEs during low-voltage conditions. When $V_{CAP} < V_{SWITCH}$, all externally initiated *STORE* operations and SRAM WRITEs will be inhibited.

AutoStore™ can be completely disabled by tying V_{CCX} to ground and applying + 5V to V_{CAP}. This is the *AutoStore*™ Inhibit mode; in this mode *STORE*s are only initiated by explicit request using either the software sequence or the $\overline{\text{HSB}}$ pin.

LOW AVERAGE ACTIVE POWER

The STK14C88 draws significantly less current when it is cycled at times longer than 50ns. Figure 5 shows the relationship between I_{CC} and READ cycle time. Worst-case current consumption is shown for both CMOS and TTL input levels (commercial temperature range, V_{CC} = 5.5V, 100% duty cycle on chip enable). Figure 6 shows the same relationship for WRITE cycles. If the chip enable duty cycle is less than 100%, only standby current is drawn when the chip is disabled. The overall average current drawn by the STK14C88 depends on the following items: 1) CMOS vs. TTL input levels; 2) the duty cycle of chip enable; 3) the overall cycle rate for accesses; 4) the ratio of READs to WRITEs; 5) the operating temperature; 6) the V_{cc} level; and 7) I/O loading.



Figure 5: I_{cc} (max) Reads



Figure 6: I_{cc} (max) Writes

ORDERING INFORMATION

STK14C88 - N 45 I

Temperature Range

Blank = Commercial (0 to 70°C)
I = Industrial (-40 to 85°C)
M = Military (-55 to 125°C)

Access Time

25 = 25ns
35 = 35ns
45 = 45ns

Package

N = Plastic 32-pin 300 mil SOIC
W = Plastic 32-pin 600 mil DIP
L = Ceramic 32-pad LCC
C = Ceramic 32-pin 300 mil CDIP
K = Ceramic 32-pin 300 mil CDIP with solder dip finish

Document Revision History

Revision	Date	Summary
0.0	December 2002	Removed 20 nsec device; Combined commercial, industrial and military; current limit resistor added for extreme power-off slew rate.