

VWEB
VWEB11
1174 48309-0
© 2004

- MPEG-1 Layer I, II and III (MP3)
- MPEG-2 Layer I and II
- 2-channel down-mixed AAC
- 2-channel down-mixed AC-3
- Sampling frequencies: 8, 16, 22.05, 24, 32, 44.1, 48 and 96 KHz.
- Bits per channel: 16, 20, 24, 32
- For S/P-DIF, 32, 44.1 and 48 KHz at 32 bits



VW2010 MPEG-1, -2, -4 Audio/Video CODEC Chip

Demultiplexing

Input

- System, program and transport stream

Output

- Program clock recovery (PCR)
- 7 output buffers: 1 video, 4 audio, 1 PSI, 1 user (subtitle, Teletext)

Graphics

- Background (solid color) plane
- MPEG video plane
- Two 32-bit ARGB (RGB with alpha-blending) or AYUV (YUV with alpha-blending) 8:8:8:8 graphics planes
- Cursor plane
- 2-, 4- or 8-bit color indexing
- 0.5X or 2X vertical scaling; arbitrary horizontal scaling on 16-pixel boundaries (letterboxing, QSIF to SIF, SIF to D1, D1 to SIF, SIF to QSIF)
- Per-pixel alpha-blending
- Deflicker filter

Interfaces

Host Interfaces

- 8- or 16-bit Motorola-style interface, or
- 16-bit Intel-style interface, or
- PCI interface: 32 bits, 33 MHz.

System Interfaces

- GPIO (general purpose input/output): 12 pins
- IDC (inter-device communications, similar to Philips I2C)
- SDRAM
- 32-bit memory interface, using 1Mx16-5 or 2Mx32-5 SDRAM
- Minimum SDRAM requirement: 4 MB for encoder, 4 MB for decoder

A/V Input Interfaces

Uncompressed Input (Encoder)

- Video: 8-bit ITU-R.BT-656
- Audio: I2S (2 each)
- VBI, user data: 8-bit video input

MPEG Bitstream Input (Decoder)

- 8-bit / 1-bit compressed data input interface (CDI)
- Host/PCI interface

A/V Output Interfaces

Compressed Output (Encoder)

- 8-bit / 1-bit compressed data output interface (CDO)
- Host/PCI interface

Uncompressed Output (Decoder)

- Video: 8-bit ITU-R.BT-656
- Audio: one I2S, and one IEC-958 S/PDIF digital audio or IEC-61937 compressed audio
- VBI, user data:
- 1-bit (serial) bitstream using IDC or GPIO interface
- Embedded in 8-bit video bitstream

General System Facts

- 162 MHz MIPS-like RISC processor with DSP extensions for multiplexing, demultiplexing, audio encoding and audio decoding
- 365-pin PBGA package; physical dimensions: 27 mm by 27 mm
- Input voltages:
- 1.8 V internal
- 3.3 V I/O
- Estimated power consumption under 1.0 W in normal operating mode; onchip power management
- Boundary scan and assembly testing compliant with IEEE 1149.1 (JTAG) and EPI EJTAG 2.0 (extended JTAG)

Applications

The VW2010 is ideally suited for the following consumer applications:

- Camcorders and network cameras
- Personal video recorder
- Set-top boxes
- PC capture devices for video capture, content creation, and display

- VCD, Super-VCD and DVD player and recorder
 - Cellular phones and PDAs
- In addition, the VW2010 is suited for the following network applications:
- Streaming video distribution over DSL, cable, ethernet, fiber and wireless networks
 - Transcoding and transrating among MPEG-1, -2, -4 and H.263
 - Video conferencing
 - Security / surveillance
 - Video-on-demand servers

Features and Benefits

Saves money and power

- Uses less than 8 MB of external SDRAM
- Uses 32-bit SDRAM interface
- Proprietary motion estimation algorithm

Decreases time to market

- Easy to setup and configure

Superior video quality

- The rate control algorithm monitors 60 different variables, which results in a more consistent GOP structure; thus, scene changes are handled well.

Superior flexibility

- Dynamically programmable frame rates, bit rates, resolution and low delay mode
- Programmable GOP structure
- Transcoding and transrating among MPEG-1, -2, -4 and H.263

Superior ingenuity

- MPEG-1, -2, -4 full-D1 interlaced encoder/decoder
- Low latency support
- MPEG-4 short header support (H.263 baseline support)