


6367255 MOTOROLA SC (DIODES/OPTO)

34C 38223 D

MICRO-T (continued)

T-31-17

MMT3798,99 — PNP **LOW CURRENT AMPLIFIER TRANSISTOR**



- designed for low-level, low-noise amplifier applications.

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector-Emitter Voltage	V_{CEO}	60	Vdc
Collector-Base Voltage	V_{CB}	60	Vdc
Emitter-Base Voltage	V_{EB}	3.0	Vdc
Collector Current — Continuous Peak	I_C	50 100	mAdc
Total Device Dissipation @ $T_A = 25^\circ\text{C}$ Derate above 25°C	P_D	250 2.0	mW mW/ $^\circ\text{C}$
Operating and Storage Junction Temperature Range	T_J, T_{stg}	-55 to +150	$^\circ\text{C}$

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Ambient	$R_{\theta JA}$	0.50	$^\circ\text{C}/\text{mW}$

ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$ unless otherwise noted)

Parameter	Test Conditions	Min	Typ	Max	Unit
-----------	-----------------	-----	-----	-----	------

OFF CHARACTERISTICS

BV_{CEO}	$I_C = 10 \text{ mAdc}, I_B = 0$	60	—	—	Vdc
BV_{CBO}	$I_C = 10 \text{ } \mu\text{Adc}, I_E = 0$	60	—	—	Vdc
I_{CBO}	$V_{CB} = 50 \text{ Vdc}, I_E = 0$	—	—	50	nAdc
I_{EBO}	$V_{BE} = 3.0 \text{ Vdc}, I_C = 0$	—	—	50	nAdc

ON CHARACTERISTICS

h_{FE}	$I_C = 10 \text{ } \mu\text{Adc}, V_{CE} = 5.0 \text{ Vdc}$	MMT3798	75	—	—	—
		MMT3799	150	—	—	—
	$I_C = 100 \text{ } \mu\text{Adc}, V_{CE} = 5.0 \text{ Vdc}$	MMT3798	150	—	450	—
		MMT3799	300	—	900	—
	$I_C = 1.0 \text{ mAdc}, V_{CE} = 5.0 \text{ Vdc}$	MMT3798	150	—	—	—
		MMT3799	300	—	—	—
	$I_C = 10 \text{ mAdc}, V_{CE} = 5.0 \text{ Vdc}$	MMT3798	125	—	—	—
		MMT3799	250	—	—	—
$V_{CE(sat)}$	$I_C = 1.0 \text{ mAdc}, I_B = 100 \text{ } \mu\text{Adc}$	—	—	0.25	Vdc	
$V_{BE(sat)}$	$I_C = 1.0 \text{ mAdc}, I_B = 100 \text{ } \mu\text{Adc}$	—	—	0.8	Vdc	

continued

6367255 MOTOROLA SC (DIODES/OPTO)

34C 38224 D

MICRO-T (continued)

MMT3798,99 (continued)

T-31-17

SMALL-SIGNAL CHARACTERISTICS

f_T	$I_C = 500 \mu\text{A}$, $V_{CE} = 5.0 \text{ Vdc}$, $f = 20 \text{ MHz}$	MMT3798 MMT3799	40 40	120 150	— —	MHz
C_{ob}	$V_{CB} = 5.0 \text{ Vdc}$, $I_E = 0$, $f = 100 \text{ kHz}$		—	2.0	4.0	pF
C_{ib}	$V_{BE} = 0.5 \text{ Vdc}$, $I_C = 0$, $f = 100 \text{ kHz}$		—	—	12	pF
NF	$I_C = 100 \mu\text{A}$, $V_{CE} = 10 \text{ Vdc}$, $R_S = 3.0 \text{ k}\Omega$, $f = 1.0 \text{ kHz}$	MMT3798 MMT3799	— —	1.5 0.8	— —	dB
	$I_C = 100 \mu\text{A}$, $V_{CE} = 10 \text{ Vdc}$, $R_S = 3.0 \text{ k}\Omega$, $f = 10 \text{ kHz}$	MMT3798 MMT3799	— —	1.0 0.8	— —	
	$I_C = 100 \mu\text{A}$, $V_{CE} = 10 \text{ Vdc}$, $R_S = 3.0 \text{ k}\Omega$, $BW = 10 \text{ Hz to } 15.7 \text{ kHz}$	MMT3798 MMT3799	— —	2.5 1.5	3.5 2.5	