

January 7, 1998

TEL:805-498-2111 FAX:805-498-3804 WEB:http://www.semtech.com

## QUICK REFERENCE DATA

- $V_R = 5 - 7.5kV$
- $I_F = 180mA$
- $t_{rr} = 300ns$
- $I_R = 0.25\mu A$


## AXIAL LEADED HERMETICALLY SEALED HIGH VOLTAGE FAST RECTIFIER DIODE

- Low reverse recovery time
- High thermal shock resistance
- Hermetically sealed with Metoxilite metal oxide
- Low switching losses
- Soft, non-snap off, recovery characteristics

### ABSOLUTE MAXIMUM RATINGS (@ 25°C unless otherwise specified)

	Symbol	F50	F75	Unit
Working reverse voltage	$V_{RWM}$	5000	7500	V
Repetitive reverse voltage	$V_{RRM}$	5000	7500	V
Average forward current (@ 55°C in oil)	$I_{F(AV)}$	← 180 →		mA
Repetitive surge current (@ 55°C)	$I_{FRM}$	← 0.25 →		A
Non-repetitive surge current ( $t_p = 8.3ms$ , @ $V_R$ & $T_{jmax}$ )	$I_{FSM}$	← 2.0 →		A
Storage temperature range	$T_{STG}$	← -65 to +175 →		°C
Operating temperature range	$T_{OP}$	← -65 to +175 →		°C

## MECHANICAL




January 7, 1998

## CHARACTERISTICS (@ 25°C unless otherwise specified)

	Symbol	F50	F75	Unit
Average forward current max. (pcb mounted; $T_A = 55^\circ\text{C}$ ) for sine wave	$I_F(\text{AV})$	← 62 →		mA
for square wave ( $d = 0.5$ )	$I_F(\text{AV})$	← 65 →		mA
Average forward current max. (unstirred oil at $55^\circ\text{C}$ ) for sine wave	$I_F(\text{AV})$	← 160 →		mA
for square wave	$I_F(\text{AV})$	← 180 →		mA
$I^2t$ for fusing ( $t = 8.3\text{mS}$ ) max.	$I^2t$	← 0.017 →		$\text{A}^2\text{S}$
Forward voltage drop max. @ $I_F = 10\text{mA}$ , $T_j = 25^\circ\text{C}$	$V_F$	← 10.0 →		V
Reverse current max. @ $V_{\text{RWM}}$ , $T_j = 25^\circ\text{C}$	$I_R$	← 0.25 →		$\mu\text{A}$
@ $V_{\text{RWM}}$ , $T_j = 100^\circ\text{C}$	$I_R$	← 5.0 →		$\mu\text{A}$
Reverse recovery time max. 50mA $I_F$ , 100mA $I_R$ . Recover to 25mA $I_{\text{RR}}$ .	$t_{\text{rr}}$	← 300 →		nS
Junction capacitance typ. @ $V_R = 5\text{V}$ , $f = 1\text{MHz}$	$C_j$	← 1.7 →		pF
Thermal resistance - junction to oil Stirred oil	$R_{\theta\text{JO}}$	← 33 →		$^\circ\text{C/W}$
Unstirred oil	$R_{\theta\text{JO}}$	← 44 →		$^\circ\text{C/W}$
Thermal resistance - junction to amb. on 0.06" thick pcb. 1oz copper.	$R_{\theta\text{JA}}$	← 134 →		$^\circ\text{C/W}$

Fig 1. Junction capacitance  
against reverse voltage.



January 7, 1998




Fig 2. Forward voltage drop as a function of forward current.




Fig 3. Power derating in air and oil.




Fig 4. Forward power dissipation as a function of forward current, for sinusoidal operation.




Fig 5. Forward power dissipation as a function of forward current, for square wave operation.