


SWITCHING APPLICATION.
INTERFACE CIRCUIT AND DRIVER CIRCUIT APPLICATION

FEATURES


- With Built-in Bias Resistors.
- Simplify Circuit Design.
- Reduce a Quantity of Parts and Manufacturing Process.

EQUIVALENT CIRCUIT




BIAS RESISTOR VALUES

TYPE NO.	R1(k Ω)	R2(k Ω)
KRA566E	1	10
KRA567E	2.2	2.2
KRA568E	2.2	10
KRA569E	4.7	10
KRA570E	10	4.7
KRA571E	47	10
KRA572E	100	100



EQUIVALENT CIRCUIT (TOP VIEW)



MAXIMUM RATING (Ta=25 °C)

CHARACTERISTIC		SYMBOL	RATING	UNIT
Output Voltage	KRA566E ~572E	V _O	-50	V
Input Voltage	KRA566E	V _I	-10, 5	V
	KRA567E		-12, 10	
	KRA568E		-12, 5	
	KRA569E		-20, 7	
	KRA570E		-30, 10	
	KRA571E		-40, 15	
	KRA572E		-40, 10	
Output Current	KRA566E ~572E	I _O	-100	mA
Power Dissipation		P _D *	200	mW
Junction Temperature		T _j	150	°C
Storage Temperature Range		T _{stg}	-55 ~ 150	°C


* : Total Rating.

MARK SPEC

TYPE	KRA566E	KRA567E	KRA568E	KRA569E	KRA570E	KRA571E	KRA572E
MARK	P2	P4	P5	P6	P7	P8	P9

Maring

Type Name









KRA566E~KRA572E

ELECTRICAL CHARACTERISTICS (Ta=25 °C)







CHARACTERISTIC		SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Cut-off Current	KRA566E ~ 572E	$I_{O(OFF)}$	$V_O = -50V, V_I = 0$	-	-	-500	nA
DC Current Gain	KRA566E	G_I	$V_O = -5V, I_O = -5mA$	33	-	-	
	KRA567E		$V_O = -5V, I_O = -20mA$	20	-	-	
	KRA568E		$V_O = -5V, I_O = -10mA$	33	-	-	
	KRA569E		$V_O = -5V, I_O = -10mA$	30	-	-	
	KRA570E		$V_O = -5V, I_O = -10mA$	24	-	-	
	KRA571E		$V_O = -5V, I_O = -5mA$	33	-	-	
	KRA572E		$V_O = -5V, I_O = -5mA$	62	-	-	
Output Voltage	KRA566E	$V_{O(ON)}$	$I_O = -10mA, I_I = -0.5mA$	-	-	-0.3	V
	KRA567E		$I_O = -10mA, I_I = -0.5mA$	-	-0.1	-0.3	
	KRA568E		$I_O = -10mA, I_I = -0.5mA$	-	-	-0.3	
	KRA569E		$I_O = -10mA, I_I = -0.5mA$	-	-0.1	-0.3	
	KRA570E		$I_O = -10mA, I_I = -0.5mA$	-	-0.1	-0.3	
	KRA571E		$I_O = -10mA, I_I = -0.5mA$	-	-0.1	-0.3	
	KRA572E		$I_O = -5mA, I_I = -0.25mA$	-	-0.1	-0.3	
Input Voltage (ON)	KRA566E	$V_{I(ON)}$	$V_O = -0.3V, I_O = -20mA$	-	-0.98	-3	V
	KRA567E		$V_O = -0.3V, I_O = -20mA$	-	-1.83	-3	
	KRA568E		$V_O = -0.3V, I_O = -20mA$	-	-1.22	-3	
	KRA569E		$V_O = -0.3V, I_O = -20mA$	-	-1.76	-2.5	
	KRA570E		$V_O = -0.3V, I_O = -2mA$	-	-2	-3	
	KRA571E		$V_O = -0.3V, I_O = -2mA$	-	-3.9	-5	
	KRA572E		$V_O = -0.3V, I_O = -1mA$	-	-1.64	-3	
Input Voltage (OFF)	KRA566E	$V_{I(OFF)}$	$V_{CC} = -5V, I_O = -100\mu A$	-0.3	-0.63	-	V
	KRA567E			-0.5	-1.15	-	
	KRA568E			-0.3	-0.67	-	
	KRA569E			-0.3	-0.82	-	
	KRA570E			-0.8	-1.68	-	
	KRA571E			-1	-3.09	-	
	KRA572E			-0.5	-1.17	-	
Transition Frequency	KRA566E ~ 572E	f_T^*	$V_O = -10V, I_O = -5mA$	-	250	-	MHz
Input Current	KRA566E	I_I	$V_I = -5V$	-	-	-7.2	mA
	KRA567E			-	-	-3.8	
	KRA568E			-	-	-3.8	
	KRA569E			-	-	-1.8	
	KRA570E			-	-	-0.88	
	KRA571E			-	-	-0.16	
	KRA572E			-	-	-0.15	

Note : * Characteristic of Transistor Only.







KRA566E~KRA572E



KRA566E~KRA572E



KRA566E~KRA572E



KRA566E~KRA572E

