

2SB1321A

Silicon PNP epitaxial planer type

For general amplification

Complementary to 2SD1992A

■ Features

- Large collector power dissipation P_C (600 mW)
- Allowing supply with the radial taping

■ Absolute Maximum Ratings $T_a = 25^\circ\text{C}$

Parameter	Symbol	Rating	Unit
Collector to base voltage	V_{CBO}	-60	V
Collector to emitter voltage	V_{CEO}	-50	V
Emitter to base voltage	V_{EBO}	-7	V
Peak collector current	I_{CP}	-1	A
Collector current	I_C	-500	mA
Collector power dissipation	P_C	600	mW
Junction temperature	T_j	150	$^\circ\text{C}$
Storage temperature	T_{stg}	-55 to +150	$^\circ\text{C}$

■ Electrical Characteristics $T_a = 25^\circ\text{C} \pm 3^\circ\text{C}$


Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Collector cutoff current	I_{CBO}	$V_{CB} = -20\text{ V}, I_E = 0$			-0.1	μA
	I_{CEO}	$V_{CE} = -20\text{ V}, I_B = 0$			-1	μA
Collector to base voltage	V_{CBO}	$I_C = -10\text{ }\mu\text{A}, I_E = 0$	-60			V
Collector to emitter voltage	V_{CEO}	$I_C = -2\text{ mA}, I_B = 0$	-50			V
Emitter to base voltage	V_{EBO}	$I_E = -10\text{ }\mu\text{A}, I_C = 0$	-7			V
Forward current transfer ratio *1	h_{FE1} *2	$V_{CE} = -10\text{ V}, I_C = -10\text{ mA}$	85		340	
	h_{FE2}	$V_{CE} = -10\text{ V}, I_C = -500\text{ mA}$	40			
Collector to emitter saturation voltage	$V_{CE(sat)}$	$I_C = -300\text{ mA}, I_B = -30\text{ mA}$		-0.35	-0.6	V
Transition frequency	f_T	$V_{CB} = -10\text{ V}, I_E = 10\text{ mA}, f = 200\text{ MHz}$		200		MHz
Collector output capacitance	C_{ob}	$V_{CB} = -10\text{ V}, I_E = 0, f = 1\text{ MHz}$		6	15	pF









Note) *1: Pulse measurement

*2: Rank classification

Rank	Q	R	S	No-rank
h_{FE1}	85 to 170	120 to 240	170 to 340	85 to 340

Product of no-rank is not classified and have no indication for rank.



$P_C - T_a$  $I_C - V_{CE}$  $I_C - I_B$  $V_{CE(sat)} - I_C$  $V_{BE(sat)} - I_C$  $h_{FE} - I_C$  $f_T - I_E$  $C_{ob} - V_{CB}$  $V_{CER} - R_{BE}$ 